




8Ω

Coaxials - 8.0 Inches







- 400 W continuous program power capacity
- 100° nominal coverage
 75 20000 Hz response
- 94 dB sensitivity
 34.5 mm (1.35") HF unit exit diameter









SPECIFICATIONS

Nominal Diameter	210 mm (8.0 in)	
Nominal Impedance	8 Ω	
Minimum Impedance LF	6.3 Ω	
Minimum Impedance HF	7.7 Ω	
Frequency Range	75 - 20000 Hz	
Dispersion Angle ¹	100 °	
Woofer Cone Treatment WP Waterproof Front Side		
Magnet Material Ceramic (LF) - Neodym. Ring (HF)		

PARAMETERS

Resonance Frequency	76 Hz
Re	5.1 Ω
Qes	0.36
Qms	5.0
Qts	0.34
Vas	11.5 dm ³ (0.4 ft ³)
Sd	220.0 cm ² (34.1 in ²)
ηο	1.4 %
Xmax	6.0 mm
Xvar	6.0 mm
Mms	25.0 g
BI	13.0 Txm
Le	1.0 mH
EBP	211 Hz

SPECIFICATIONS LF UNIT

LF Sensitivity ²	94.0 dB
LF Nominal Power Handling	3 200 W
LF Continuous Power Handl	ing ⁴ 400 W
LF Voice Coil Diameter	52 mm (2.0 in)
LF Winding Material	Copper
LF Flux Density	1.05 T
Former Material	Kapton
Winding Depth	16.5 mm (0.65 in)
Magnetic Gap Depth	8.0 mm (0.31 in)

MOUNTING AND SHIPPING INFO

Overall Diameter	225 mm (8.8 in)
Bolt Circle Diameter	210 mm (8.3 in)
Baffle Cutout Diameter	187 mm (7.4 in)
Depth	129 mm (5.1 in)
Flange and Gasket Thickness	11 mm (0.4 in)
Net Weight	3.9 kg (8.6 lb)
Shipping Weight	4.5 kg (9.92 lb)

Shipping Box 295x314x175 mm (11.61x12.36x6.89 in)

SPECIFICATIONS HF UNIT

HF Sensitivity ⁵	103.0 dB
HF Nominal Power Handling ⁶	50 W
HF Continuous Power Handling ⁷	100 W
HF Voice Coil Diameter	44 mm (1.7 in)
HF Winding Material	Aluminium
HF Flux Density	1.8 T
Diaphragm Material	Titanium
Recommended Crossover ⁸	2.0 kHz
Inductance	0.11 mH

SERVICE KIT

Service Kit LF	RCK008CXT8
Replacement diaphragm	MMD400TN8

Included by -6 dB down points.
 Applied RMS Voltage is set to 2.83V.
 2 hours test made with continuous pink noise signal within the range Fs-10Fs. Power calculated on rated nominal impedance. Loudspeaker in free air.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 Applied RMS Voltage is set to 2.83V.
 2 hour test made with continuous pink noise signal within the range from the recommended crossover frequency to 20 kHz. Power calculated on rated nominal impedance. Loudspeaker in free air.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 12 dB/oct. or higher slope high-pass filter.

B&C Speakers s.p.a.

Via Poggiomoro, 1 - Loc. Vallina, 50012 Bagno a Ripoli (FI) - ITALY - Tel. +39 055 65721 - Fax +39 055 6572312 - mail@bcspeakers.com